


CET4-AR-CRA-AH-50X-SG-C2333-120246 (Order no. 120246)

Safety switch with guard locking CET-AR-..., RFID, plug connector(s) M12, lockout bar

- ▶ Open-circuit current principle
- ▶ Unicode
- ▶ Teach-in input J
- ▶ Monitoring output guard locking OUT
- ▶ Monitoring output door position OUT D
- ▶ 2 x plug connectors(s) M12, 5-pin and 8-pin
- ▶ Lockout mechanism



Approach direction



Horizontal

Can be adjusted in 90° steps

Guard locking principle

Open-circuit current (power on to lock): On a guard with guard locking based on the open-circuit current principle, the guard is locked until the power supply to the guard locking solenoid is interrupted.

Unlocking is by spring force. The term electrical guard locking is also used.

Unicode evaluation

Each actuator is highly coded (unicode). The switch detects only taught-in actuators. Additional actuators can be taught-in.

Only the last actuator taught-in is detected.

Safety characteristics

Thanks to two redundant safety outputs (semiconductor outputs) with internal monitoring, the device is suitable for:

- ▶ Category 4 /PL e according to EN 13849-1
- ▶ SIL 3 according to EN IEC 62061 Table 4

The OSSD outputs used check their function for short circuits and short circuits with test pulses.

Lockout mechanism

The lockout bar can be used to prevent maintenance personnel from being unintentionally locked in the danger zone, for example.

Important: The lockout bar is not a safety function..

This device with lockout bar possesses no auxiliary release.

LED indicator




LED STATE Status LED

DIA LED Diagnostics LED

LED 1 rd freely configurable

LED 2 gn illuminates when door is closed

Terminal assignment

Plug connector (view of connection side)	Pin	Designation	Function	Connecting cable conductor coloring
	X 1.1	IB	Enable input, channel B	WH
	X 1.2	UB	Electronics operating voltage, 24 V DC	BN
	X 1.3	OA	Safety outputs channel A 	GN
	X 1.4	OB	Safety outputs channel B 	YE
	X 1.5	OUT	Guard lock monitoring output	GY
	X 1.6	IA	Enable input, channel A	PK
	X 1.7	0 V UB	Electronics operating voltage, 0 V DC	BU
	X 1.8	RST	Reset input	RD
	X 2.1	0 V UCM	Solenoid operating voltage, 0 V DC	BN
	X 2.2	OUT D	Door position monitoring output	WH
	X 2.3	LED 1	LED 1 red, freely assignable, 24 V DC	BU
	X 2.4	UCM	Solenoid operating voltage, 24 V DC	BK
	X 2.5	J	Teach-in input	GY

Accessories required

Actuator is not included.