

## CET3-AP-CRA-AH-50F-SI-C2357-114626 (Order no. 114626)

**Safety switch with guard locking CET-AP-..., RFID, plug connector M12, escape release, lockout bar, for connection to decentralized peripheral systems**


- ▶ Closed-circuit current principle
- ▶ Unicode
- ▶ 2 x plug connector(s) M12, 5-pin
- ▶ for connection to decentralized peripheral systems
- ▶ Escape release, 105 mm long
- ▶ Lockout mechanism



### Direct connection to decentralized peripheral systems

The connection via M12 plug connector(s) is optimized for direct connection to IP67 IO modules, such as ET200pro and ET200eco from SIEMENS, MVK from MURR and EP1957 from BECKHOFF.

### Approach direction



Horizontal

Can be adjusted in 90° steps

### Guard locking principle

Power to unlock: On a guard with guard locking based on the closed-circuit current principle, the guard is locked by spring force until the guard locking solenoid is supplied with power. Unlocking is by solenoid force. The term mechanical guard locking is also used.

### Unicode evaluation

Each actuator is highly coded (unicode). The switch detects only taught-in actuators. Additional actuators can be taught-in.

Only the last actuator taught-in is detected.

## Safety characteristics

Thanks to two redundant safety outputs (semiconductor outputs) with internal monitoring, the device is suitable for:

- ▶ Category 4 /PL e according to EN 13849–1
- ▶ SIL 3 according to EN IEC 62061 Table 4

The OSSD outputs used check their function for short circuits and short circuits with test pulses.

## Escape release

This is used for manual release of guard locking from the danger zone without tools.

## Lockout mechanism

The lockout bar can be used to prevent maintenance personnel from being unintentionally locked in the danger zone, for example.

**Important:** The lockout bar is not a safety function..

This device with lockout bar possesses no auxiliary release.

## LED indicator


LED STATE Status LED

DIA LED Diagnostics LED

LED 1 rd illuminates when the solenoid is energized

LED 2 gn illuminates when door is closed

## Terminal assignment

Plug connector (view of connection side)	Pin	Designation	Function	Connecting cable conductor coloring
	X 1.1	UB	Electronics operating voltage, 24 V DC	BN
	X 1.2	OA	Safety output, channel A	WH
	X 1.3	0 V	Electronics operating voltage, 0 V DC	BU
	X 1.4	OB	Safety output, channel B	BK
	X 1.5	–	n.c.	GY
	X 2.1	–	n.c.	BN
	X 2.2	–	n.c.	WH
	X 2.3	0VUCM	Solenoid operating voltage, 0 V DC	BU
	X 2.4	UCM	Solenoid operating voltage, 24 V DC	BK
	X 2.5	–	n.c.	GY

## Accessories required

Actuator is not included.

The safety switch can only be actuated in conjunction with the actuators provided for this purpose.