

Discrete Input Modules



Discrete input modules receive signals from input devices such as sensors, pushbuttons, and switches that can have two states: on or off, open or closed. Modules require a carrier base (IC200CHSxxx).

	IC200MDL140	IC200MDL141	IC200MDL143
Product Name	VersaMax Discrete Input Module 120 VAC, 8 points	VersaMax Discrete Input Module 240 VAC, 8 points	VersaMax Discrete Input Module 120 VAC Isolated, 8 points
Lifecycle Status	Active	Active	Active
Input Voltage	0-132 VAC	0-264 VAC	0-132 VAC
Number of Points	8	8	8
Channel to Channel Isolation	No	No	Yes
Input and Output Response Time- On/Off (ms)	1 cycle/2 cycles	1 cycle/2 cycles	1 cycle/2 cycles
Points per Common	1 group of 8	1 group of 8	8 groups of 1
On State Current	5 mA minimum	7 mA minimum	5 mA minimum
Off State Current	2.5 mA maximum	1.5 mA maximum	2.5 mA maximum
Input Impedance	8.6 kOhms (reactive) at 60 Hz, typical; 10.32 kOhms (reactive) at 50 Hz, typical	38.5 kOhms (reactive) at 60 Hz, typical; 46.3 kOhms (reactive) at 50 Hz, typical	8.6 kOhms (reactive) at 60 Hz, typical; 10.32 kOhms (reactive) at 50 Hz, typical
5V Backplane Current Consumption (mA)	55 maximum	55 maximum	50 maximum
LED Indicators	One LED per point shows individual point ON/OFF status. OK LED indicates backplane power is present	One LED per point shows individual point ON/OFF status. OK LED indicates backplane power is present	One LED per point shows individual point ON/OFF status. OK LED indicates backplane power is present
Dimensions (W x H x D)	110 mm (4.3 in) x 66.8 mm (2.63 in) x 50 mm (1.956 in), not including the height of the carrier or the mating connectors	110 mm (4.3 in) x 66.8 mm (2.63 in) x 50 mm (1.956 in), not including the height of the carrier or the mating connectors	110 mm (4.3 in) x 66.8 mm (2.63 in) x 50 mm (1.956 in), not including the height of the carrier or the mating connectors