

Analog Expansion Units



The VersaMax Micro analog I/O is versatile and the Micro PLC can support up to four Analog Expansion Units, allowing you to expand up to 16 inputs and 8 outputs.

	IC200UEX624	IC200UEX616	IC200UEX626	IC200UEX636
Product Name	4 Analog I/O Channels 0 to 10VDC, 4 to 20mA, 24 VDC Powered	6 Analog I/O Channels (4) 0 to 10 VDC, ± 10 VDC, 4 to 20 mA, 0 to 20 mA In, (2) 0 to 10 VDC, 4 to 20 mA, 0 to 20 mA Out, 12 VDC Powered	6 Analog I/O Channels (4) 0 to 10 VDC, ± 10 VDC, 4 to 20 mA, 0 to 20 mA In, (2) 0 to 10 VDC, 4 to 20 mA, 0 to 20 mA Out, 24 VDC Powered	6 Analog I/O Channels (4) 0 to 10 VDC, ± 10 VDC, 4 to 20 mA, 0 to 20 mA In, (2) 0 to 10 VDC, 4 to 20 mA, 0 to 20 mA Out, 120/240 VAC Powered
Lifecycle Status	Active	Active	Active	Active
Micro Type Restrictions	N/A	N/A	N/A	N/A
Number of Analog Inputs/Outputs	4 Channels In, Voltage or Current	4 Channels In / 2 Channels Out, Voltage or Current	4 Channels In / 2 Channels Out, Voltage or Current	4 Channels In / 2 Channels Out, Voltage or Current
Power Voltage	24 VDC	12 VDC	24 VDC	120/240 VAC
Input Power Supply Rating	3 Watts	2.25 Watts	3 Watts	15 VA
24 VDC User Power for Sensors	200 mA	200 mA	200 mA	200 mA
Analog Input Ranges	0-10V (10.23V Max); 0- ± 10 V (± 10.23 V Max); 0-20 mA (20.47 mA Max); 4-20 mA; 12 bit resolution.	0-10V (10.23V Max); 0- ± 10 V (± 10.23 V Max); 0-20 mA (20.47 mA Max); 4-20 mA; 12 bit resolution.	0-10V (10.23V Max); 0- ± 10 V (± 10.23 V Max); 0-20 mA (20.47 mA Max); 4-20 mA; 12 bit resolution.	0-10V (10.23V Max); 0- ± 10 V (± 10.23 V Max); 0-20 mA (20.47 mA Max); 4-20 mA; 12 bit resolution.
Analog Output Ranges	N/A	0 to 10 VDC (10.24V max.) 0 to 20 mA (20.5 mA max.) 4 to 20 mA (20.5 mA max.); 12 bit resolution.	0 to 10 VDC (10.24V max.) 0 to 20 mA (20.5 mA max.) 4 to 20 mA (20.5 mA max.); 12 bit resolution.	0 to 10 VDC (10.24V max.) 0 to 20 mA (20.5 mA max.) 4 to 20 mA (20.5 mA max.); 12 bit resolution.
Dimensions (WxHxD) mm	95x90x76	95x90x76	95x90x76	95x90x76