

Date:	Project Name:
Type:	Part Number:



EMERGENCY SERIES

LED EMERGENCY BATTERY





DESCRIPTION

These battery units are designed with a rugged metal frame and sporting double swivel positioning heads on top to provide bright illumination. Easy knockouts provided for swift installation on each jobsite.

FEATURES

- 120/277/347V input
with any emergency lighting system (5-24VDC)
- Lead Acid Battery
- 2x2W LED HEADS /2x5W LED HEADS
- cULus Listed
- Self-powered for 120 minutes
- Max remote load :
72W at 30 mins battery backup time
27W at 90 mins battery backup time
22W at 120 mins battery backup time
- 5 year warranty

APPLICATIONS

-  Commercial building
-  Multi-Residential building



Date:	Project Name:
Type:	Part Number:

SPECIFICATION

ORDER#	MODEL#	WATTS	VOLTAGE (V)	INPUT	OUTPUT
R61201	RENO-EBP36W-U	36W	3.6V-24VDC	120/277/347V	6 VDC
R61202	RENO-EBP72W-U	72W	5V-24VDC	120/277/347V	12 VDC

REMOTE HEAD OPTIONS

ORDER#	MODEL#	DESCRIPTION
R61101	RENO-ERH2W-1	2W LED Head
R61102	RENO-ERH7W-1	7W LED Head
R61103	RENO-ERH2W-2	2x2W LED Heads
R61105	RENO-ERH5W-2	2 x5W LED Heads