


STA3A-2131A024L024BHA10C2398 (Order no. 119366)

Safety switch STA, plug connector BHA (MR10), contacts for the door position, escape release

- ▶ Plug connector BHA (MR10)
- ▶ Contacts for the door position
- ▶ Auxiliary release
- ▶ Escape release, long
- ▶ LED indicator
- ▶ Closed-circuit current principle



Approach direction



Horizontal and vertical

Can be adjusted in 90° steps

Increased overtravel for horizontal approach direction

If increased play is required when the door is closed, an actuator with overtravel is available. With this actuator the door can move slightly in the actuating direction when closed. This is important, for example, if safety doors have a rubber end stop. Using an actuator with overtravel, the continuous pressure from the compressed rubber can be reduced. In this way the load is reduced on the switch head and the door mechanism.

LED indicator

The switch has two freely assignable LED indicators (red and green).

Guard locking principle

Power to unlock: On a guard with guard locking based on the closed-circuit current principle, the guard is locked by spring force until the guard locking solenoid is supplied with power. Unlocking is by solenoid force. The term mechanical guard locking is also used.

Switching element

2131 Slow-action switching contact

Contacts for guard locking: 2 positively driven contacts  + 1 NO contact

Contacts for door monitoring: 1 NC contact

Auxiliary release

The auxiliary release on the front makes it possible to access the machine if there is a malfunction, e.g. a power failure. Unlocking is performed using a tool or a key. The auxiliary release must be protected against misuse (sealing, lacquer).

Escape release

This is used for manual release of guard locking from the danger zone without tools.

Accessories required

Actuator is not included.

Functional drawings

