


CTP-L2-AP-U-HA-AE-SA-136841 (Order no. 136841)

Safety switch with guard locking CTP-AP, RFID, plug connector M12, escape release

- ▶ Open-circuit current principle
- ▶ Unicode
- ▶ Monitoring output door position OD
- ▶ Monitoring output diagnosis OI
- ▶ Plug connector M12, 8-pin
- ▶ Escape release



Approach direction



Horizontal

Can be adjusted in 90° steps

Guard locking principle

Open-circuit current (power on to lock): On a guard with guard locking based on the open-circuit current principle, the guard is locked until the power supply to the guard locking solenoid is interrupted.

Unlocking is by spring force. The term electrical guard locking is also used.

Unicode evaluation


Each actuator is highly coded (unicode). The switch detects only taught-in actuators. Additional actuators can be taught-in.

Only the last actuator taught-in is detected.

Escape release

This is used for manual release of guard locking from the danger zone without tools.

Terminal assignment

Plug connector (view of connection side)	Pin	Designation	Function	Connecting cable conductor coloring
	1	IMP	Operating voltage of guard locking solenoid, 24 V DC	WH
	2	UB	Electronics operating voltage, 24 V DC	BN
	3	FO1A	Safety outputs channel A 	GN
	4	FO1B	Safety outputs channel B 	YE
	5	OI	Diagnostic monitoring output	GY
	6	OD	Door position monitoring output	PK
	7	0 V UB	Electronics operating voltage, 0 V DC	BU
	8	IMM	Solenoid operating voltage, 0 V DC	RD

Accessories required

Actuator is not included.

The safety switch can only be actuated in conjunction with the actuators provided for this purpose.