

CTP-L1-AR-U-HA-AZS-SAB-160862 (Order no. 160862)

Safety switch with guard locking CTP-AR, RFID, plug connector(s) M12, stainless steel


- ▶ Closed-circuit current principle
- ▶ Unicode
- ▶ Monitoring output door position OD
- ▶ Monitoring output diagnosis OI
- ▶ Guard lock monitoring output OL
- ▶ 2 x plug connector(s) M12, 5-pin and 8-pin
- ▶ ECOLAB certificate
- ▶ Version with stainless-steel components



medium-resistant stainless-steel version

robust, tough and largely media resistant. Critical components such as plugs, cover screws and guide bushes, etc., consist of high-quality inox steel.

Approach direction



Horizontal

Can be adjusted in 90° steps

Guard locking principle


Power to unlock: On a guard with guard locking based on the closed-circuit current principle, the guard is locked by spring force until the guard locking solenoid is supplied with power. Unlocking is by solenoid force. The term mechanical guard locking is also used.

Unicode evaluation

Each actuator is highly coded (unicode). The switch detects only taught-in actuators. Additional actuators can be taught-in.

Only the last actuator taught-in is detected.

Terminal assignment

Plug connector (view of connection side)	Pin	Designation	Function	Connecting cable conductor coloring
	X 1.1	FI1B	Enable input, channel B	WH
	X 1.2	UB	Electronics operating voltage, 24 V DC	BN
	X 1.3	FO1A	Safety outputs channel A 	GN
	X 1.4	FO1B	Safety outputs channel B 	YE
	X 1.5	OL	Guard lock monitoring output	GY
	X 1.6	FI1A	Enable input, channel A	PK
	X 1.7	0 V UB	Electronics operating voltage, 0 V DC	BU
	X 1.8	RST	Reset input	RD
	X 2.1	IMM	Solenoid operating voltage, 0 V DC	BN
	X 2.2	OD	Door position monitoring output	WH
	X 2.3	OI	Diagnostic monitoring output	BU
	X 2.4	IMP	Electronics operating voltage, 24 V DC	BK
	X 2.5	–	n.c.	GY

Accessories required

Actuator is not included.

The safety switch can only be actuated in conjunction with the actuators provided for this purpose.