









A2 Side Mount Auxiliary Contact Blocks (1 & 2 Pole) ❶

CA7 Contactors

Contact Block	Description	NO	NC	Contact Arrangement	For use with...	Catalog Number ❸
 <p>1-pole (typical)</p>  <p>2-pole (typical)</p>	Auxiliary Contact Blocks for Side Mounting - ❶ <ul style="list-style-type: none"> • 1 and 2-pole • Two way numbering for right or left mounting on the contactor • Snap-on design - mounts without tools • Electronic compatible contacts down to 24V, 20mA • Late break / early make (L) available • Mutual positive guidance to the main contactor poles (excluding L-types) 	0	1		CA7 all	CA7-PA-01
		1	0		CA7 all ❷	CA7-PA-10
		0	2		CA7 all	CA7-PA-02
		1	1		CA7 all ❷	CA7-PA-11
		2	0		CA7 all ❷	CA7-PA-20
		1EM	1LB		CA7 all	CA7-PA-L11

❶ Max. number of auxiliary contacts that may be mounted:

- AC Coil contactors - max. 4 N.O. contacts on the front of the contactor, 2-N.O. contacts on the side, 4-N.C. front or side: 6 total.
- DC Coil contactors - max. 4 N.O. contacts on the front of the contactor, or max. 2-N.O. contacts on side, 4-N.C. front or side: (4) total.

❷ Left mounting only is recommended when using with CA7-9...CA7-23 contactors. These contactors have built-in auxiliaries, which will result in duplicate terminal markings if mounted on the right.

❸ Detailed ratings can be found on page A2:47.