

Eaton PDG23K0225TFFJ

Catalog Number: PDG23K0225TFFJ

Eaton Power Defense molded case circuit breaker, Globally Rated, Frame 2, Three Pole, 225A, 50kA/480V, T-M (Fxd-Fxd) TU, Standard Line and Load (PDG2X3TA225)

General specifications

Product Name	Catalog Number
Eaton Power Defense molded case circuit breaker	PDG23K0225TFFJ
	UPC
	786679246344
Product Length/Depth	Product Height
88.9 mm	152.4 mm
Product Width	Product Weight
104.6 mm	1.82 kg
Warranty	Compliances
Eaton Selling Policy 25-000, one (1) year RoHS Compliant from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.	Certifications
	CSA IEC 60947-2 UL 489 CCC Marked



Product specifications

Interrupt rating

50 kAIC at 480 Vac

Frame

2

Rated operation voltage (Ue) at AC - max

600

Amperage Rating

225 A

Number of poles

Three-pole

Voltage rating - max

600 V

Circuit breaker type

PD2 Global

Interrupt rating range

30/25 kAIC Icu/ 15/13 kAIC Ics @525V South Africa (IEC)

10 kAIC Icu @125 Vdc

25 kAIC @600V (UL/CSA)

10 kAIC Icu @250 Vdc

35 kAIC Icu/ 22.5 kAIC Ics/ 73.5 kAIC Icm @480V Brazil (IEC)

85 kAIC @240V (UL)

85 kAIC Icu/ 85 kAIC Ics/ 187 kAIC Icm @240V (IEC)

10 kAIC Icu/ 5 kAIC Ics/ 21 kAIC Icm @690V (IEC)

35 kAIC Icu/ 35 kAIC Ics/ 73.5 kAIC Icm @440V (IEC)

50 kAIC @480V (UL)

50 kAIC Icu/ 50 kAIC Ics/ 105 kAIC Icm @380-415V (IEC)

Switch off technique

Thermomagnetic

Class

Class A

Circuit breaker frame type

Complete breaker

Terminals

Standard Line and Load

Voltage rating

600 Vac

Trip Type

T-M (Fxd-Fxd) TU

Resources

3D CAD drawing package

Eaton Power Defense MCCB PDG23K0225TFFJ 3D drawing

Application notes

Consulting application guide - molded case circuit breakers

Brochures

Power Defense molded case circuit breaker selection poster

Power Defense brochure

Power Defense technical selling booklet

Power Defense molded case circuit breakers - Frame 2 product aid

Catalogs

Molded case circuit breakers catalog

Certification reports

PDG4 CCC certification

PDG4 CB report

EU Declaration of Conformity - Power Defense molded case circuit breakers

Power Defense Declaration concerning California's Proposition 65

PDG2 CB report

Installation instructions

Power Defense Frame 2 tunnel terminal kits - PDG2X1TA225K instructions- IL012239EN H01

Power Defense Frame 1-2-3-4 IP door barrier assembly instructions - IL012278EN

Power Defense Frame 2 handle mech variable depth rotary handle instructions - IL012136EN

Power Defense Frame 2 handle mech direct rotary handle instructions - IL012134EN

Power Defense Frame 2 locking devices and handle block instructions - IL012149EN

Power Defense Frame 2 shunt trip UVR instructions - IL012130EN

Power Defense Frame 2 clamp terminal (steel), 20A, 3 pole instructions - IL012246EN H03

Power Defense Frame 2 multi wire connector kit - PDG2X3(2)(4)TA2253W instructions - IL012243EN H01

Power Defense Frame 2/3/4/5/6 voltage neutral sensor module wiring instructions - IL012316EN

Power Defense Frame 2 screw terminal_end cap kit, 225A, 3 pole instructions - IL012258EN H01

Power Defense Frame 2 Direct Rotary Handle Assy With Interlock Version
Instructions (IL012138EN).pdf

Power Defense Frame 2 terminal kit - PDG2X3(2)(4)TA225RF
instructions - IL012245EN H01

Power Defense Frame 2 tunnel terminal (aluminum), 50A, 3 pole
instructions - IL012236EN H03

Power Defense Frame 1 IEC and Frame 2 Rotary Mechanism with NFPA
Handle Attachment Instructions (IL012260EN).pdf

Power Defense Frame 2 PDG2 and PDC(E)9 breaker instructions -
IL012106EN

Power Defense Frame 2 multi wire connector kit -
PDG2X3(2)(4)TA2256W instructions - IL012242EN H01

Power Defense Frame 2 box terminal (aluminum), 225A, 3 pole
instructions - IL012235EN H03

Power Defense Frame 2 box terminal (steel), 100A, 3 pole instructions -
IL012234EN H03

Power Defense Frame 2 tunnel terminal (aluminum), 100A, 3 pole
instructions - IL012237EN H03

Power Defense Frame 2 global terminal shield, 3 pole - IL012330EN

Power Defense Frame 2 tunnel terminal (aluminum), 150A, 3 pole
instructions - IL012238EN H03

Power Defense Frame 2 terminal kit - PDG2X3(2)(4)TA150RF
instructions - IL012244EN H01

Installation videos

Power Defense Frame 2 Handle Mech Variable Depth Rotary Handle
Animated Instructions.rh

Power Defense Frame 2 Bell Alarm with PXR Animated Instructions.pdf.rh

Power Defense Frame 2 withTMTU, Shunt Trip_UVR Animated
Instructions.rh

Power Defense Frame 2 TMTU Aux, Alarm, ST and UVR Animated
Instructions.rh

Power Defense Frame 2 Locking Devices and Handle Block Animated
Instructions.pdf.rh

Multimedia

Power Defense Frame 3 Variable Depth Rotary Handle Mechanism
Installation How-To Video

Power Defense Frame 2 Variable Depth Rotary Handle Mechanism
Installation How-To Video

Power Defense Frame 2 Direct Rotary Handle Mechanism Installation
How-To Video

Power Defense Frame 2 Aux, Alarm, Shunt Trip, and UVR How-To Video

Power Defense Frame 5 Trip Unit How-To Video

[Eaton Power Defense for superior arc flash safety](#)

[Power Defense Breakers](#)

[Power Defense Frame 6 Trip Unit How-To Video](#)

[Power Defense molded case circuit breakers](#)

[Time/current curves](#)

[Power Defense time current curve Frame 2 - PD2](#)

[White papers](#)

[Molded case and low-voltage power circuit breaker health](#)

[Single and double break MCCB performance revisited](#)

[Making a better machine](#)

[Intelligent circuit protection yields space savings](#)

[Safer by design: arc energy reduction techniques](#)

[Molded case and low-voltage breaker health](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)