

# Eaton FAZ-C8/4

Catalog Number: FAZ-C8/4

Eaton FAZ supplementary protector, UL 1077 Industrial miniature circuit breaker - supplementary protector, Medium levels of inrush current are expected, 8 A, 15 kAIC, Four-pole, 5-10X /n, 50-60 Hz, Standard terminals, C Curve



## General specifications

<b>Product Name</b>	<b>Catalog Number</b>
Eaton FAZ supplementary protector	FAZ-C8/4
<b>EAN</b>	<b>Product Length/Depth</b>
4015082790561	2.76 in
<b>Product Height</b>	<b>Product Width</b>
2.76 in	2.9 in
<b>Product Weight</b>	<b>Warranty</b>
0.5 lb	1 year
<b>Certifications</b>	<b>Catalog Notes</b>
CSA Std. C22.2 No.235 IEC 60947-2 UL 1077	Positioned for medium inrush startup currents to provide protection for small transformers and pilot devices.

## Physical Attributes

### Number of poles

Four-pole

### Terminals

Standard

### Type

UL 1077 Industrial miniature circuit breaker - supplementary protector

## Performance Ratings

### Amperage Rating

8 A

### Circuit protection

C curve

### Frequency rating

50-60 Hz

### Interrupt rating

15 kAIC

### Trip Type

5-10X /n

## Miscellaneous

### Application

Suitable for applications where medium levels of inrush current are expected

## Resources

### Brochures

[Industrial miniature circuit breakers UL 489](#)

### Catalogs

[Eaton's Volume 4—Circuit Protection](#)

### Specifications and datasheets

[Eaton Specification Sheet - FAZ-C8/4](#)

[Product Data Sheet - FAZ-C8/4](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)