

Eaton FAZ-C1{3}-NA

Catalog Number: FAZ-C1/3-NA

Eaton FAZ branch protector,UL 489 Industrial miniature circuit breaker - supplementary protector,Medium levels of inrush current are expected,1 A,10 kAIC, 14 kAIC,Three-pole,277/480 V,5-10X /n,50-60 Hz,Screw terminals,C Curve

General specifications



Product Name
Eaton FAZ branch protector

Catalog Number
FAZ-C1/3-NA

EAN
4015081021147

Product Length/Depth
2.1 in

Product Height
4.13 in

Product Width
2.97 in

Product Weight
1 lb

Warranty
1 year

Certifications
CSA Std. C22.2 No. 235
UL 489

Catalog Notes
Positioned for medium inrush startup currents to provide protection for small transformers and pilot devices.

Physical Attributes

Number of poles

Three-pole

Terminals

Screw

Type

UL 489 Industrial miniature circuit breaker - supplementary protector

Performance Ratings

Amperage Rating

1 A

Circuit protection

C curve

Frequency rating

50-60 Hz

Interrupt rating

10 kAIC

14 kAIC

Trip Type

5-10X /n

Voltage rating

277/480V

Miscellaneous

Application

Suitable for applications where medium levels of inrush current are expected

Resources

Brochures

[Industrial miniature circuit breakers UL 489](#)

Catalogs

[Eaton's Volume 4—Circuit Protection](#)

Specifications and datasheets

[Product Data Sheet - FAZ-C1/3-NA](#)

[Eaton Specification Sheet - FAZ-C1/3-NA](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com
© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)