

Eaton FAZ-XAM002

Catalog Number: FAZ-XAM002

Eaton FAZ auxiliary trip indicating contact,UL 1077 Industrial miniature circuit breaker accessory - auxiliary trip indicating contact,4 A,15 kAIC,230 V,Trip-indicating,50-60 Hz,IEC: IP20

General specifications



Product Name

Eaton FAZ auxiliary trip indicating contact

Catalog Number

FAZ-XAM002

EAN

4015082624149

Product Length/Depth

0.25 in

Product Height

3.25 in

Product Width

2 in

Product Weight

1 lb

Warranty

1 year

Compliances

CE Marked

Certifications

UL 1077
IEC 60947-2
EN 60947-2
EN 60898
CSA Std. C22.2 No. 235
IEC 60898

Catalog Notes

Small selector screw changes mode. 2 Form C (changeover) contacts. Installs left side of FAZ/shunt trip. Aux contacts switch when FAZ is tripped electrically or manually. Trip indicating contact switches only when FAZ tripped electrically

Performance Ratings

Amperage Rating

4 A

Frequency rating

50-60 Hz

Trip Type

Trip-indicating

Voltage rating

250 V

Resources

Brochures

[Industrial miniature circuit breakers UL 489](#)

Catalogs

[Eaton's Volume 4—Circuit Protection](#)

Specifications and datasheets

[Product Data Sheet - FAZ-XAM002](#)

[Eaton Specification Sheet - FAZ-XAM002](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



Eaton.com/socialmedia